

### 功能操作

开/关机:长按电源键约3秒并松开,蓝灯快闪3次,开机或关机 复位: 任意状态下长按电源键约10秒

USB DAC模式: 开机状态接电脑,选择相关音频设备输出,然后播放

固件升级:具体操作请参考: https://www.fiio.com/supports

★ BTR3K支持4段CTIA耳机。

★ 同时连接蓝牙和USB DAC播放时,蓝牙播放优先,如需USB DAC音 源输出,需先暂停蓝牙端播放。


进入配对模式:

1、未配对过情况下: 开机后自动进入配对状态, 红蓝灯交替快闪; 2、强制进入配对模式: 开机后长按A约5秒, 红蓝灯交替闪烁;

3、清除配对: 开机状态下, 同时按住B和C按键约5秒;

4、同时连接两部手机: BTR3K与手机1成功连接后,长按A约5秒使

Bluetooth Headphone Amplifier **Buttons and Ports labeled/Operation explained** 



3.5mm headphone port 2.5mm headphone port

# **Functions & Operations**

Power on/off: Hold the Power button for about 3 seconds until the blue light flashes for three times, and the device will then power  $% \left\{ 1,2,...,n\right\}$ 

Reset: Hold the Power button for about 10 seconds at any time. USB DAC mode:Turn on the device and connect it to the computer, and then select it as the default audio output device to

Firmware upgrade: Please go to https://www.fiio.com/supports to get the detailed instruction.

- ★ The BTR3K supports the headphones with TRRS connectors conforming to the Apple Standard (CTIA).
- ★ When pairing to device via Bluetooth and using USB DAC function at the same time, Bluetooth connection takes priority. Please pause the Bluetooth playback when using USB DAC function.

简体中文 蓝牙耳机功率放大器

BTR3K再次进入配对状态,用手机2搜索BTR3K并连接成功后,在手机 1蓝牙设置界面点击已配对的设备"FiiO BTR3K"回连即可。也可以在 手机2与BTR3K连接成功后,将BTR3K关机,再开机,同时连接到手机 1和手机2;

5、最多支持两台手机同时连接到BTR3K。

1、失去连接后,蓝灯每两秒快闪2次,短按A即可回连 2、设备关机再开机后会自动回连上一次连接设备

连接配对成功后的按键操作:

播放/暂停/通话/挂断/取消呼叫: 短按A

**拒接来电:** 有来电时长按A约2秒

音量加/减:短按B或C 音乐换曲:按住B或C并保持不放约2秒

输入设备切换:连接两个输入设备时,要切换另外一台输入设备播 放,需先暂停当前播放的设备,再手动到另一台设备上开启播放(如

果已经在播放则会自动切换) 打开Siri: 双击A

# 指示灯显示

1、状态指示灯显示(非播放状态)

| 蓝牙状态<br>电池状态 | 待配对      | 待回连       | 已连接<br>未播放           | 播放            |
|--------------|----------|-----------|----------------------|---------------|
| 1、低电         | 红灯指示工作状态 |           |                      | 7111737       |
| 2、充电中        | 红蓝灯      | 2秒快闪2次(蓝灯 | 01217(1 32.7( (ши/-3 | 相应编码<br>指示灯常亮 |
| 3、常态         | 交替闪      | 蓝灯每2秒     | 蓝灯每3秒                | 相应编码          |
| 4、充电完成       |          | 快闪2次      | 快闪1次                 | 指示灯呼吸         |

### 2、编码方式工作指示灯显示(已连接播放状态)

| 编码格式         | 指示灯颜色 |
|--------------|-------|
| SBC          | 蓝灯呼吸  |
| AAC          | 青蓝灯呼吸 |
| aptX、aptX LL | 紫灯呼吸  |
| aptX HD      | 黄灯呼吸  |
| LDAC         | 白灯呼吸  |

# **Enter pairing mode**

1. After powered on for the first time: the device would automatically enter the pairing mode, and the red and blue lights  $% \left( 1\right) =\left( 1\right) \left( 1\right) \left$ will flash alternately

2. Force the device to enter Pairing mode: Hold the button A for about 5 seconds when the device is on, and the red and blue lights will flash alternately.

Bluetooth Headphone Amplifier

 ${\bf 3.\,Clear\,current\,pairing:}$  Hold the button B and C at the same time for about 5 seconds when the device is on.

4. How to use the BTR3K with two Bluetooth devices simultaneously: after a successful pairing with device1, hold the button A for around 5 seconds to enter pairing mode. Search for BTR3K on the device2 and pair it with the BTR3K.On device1,select BTR3K in the device list and reconnect. You could also restart the BTR3K after a successful pairing with device2 in order to use the BTR3K with two Bluetooth devices simultaneously.

5. The BTR3K supports connecting with two devices at the same

# Enter reconnecting mode

1. After disconnection, the blue light will flash twice every two seconds; click the button A to reconnect. 2. After the device restarted, it will reconnect to the last connected

device automatically. Operation instruction after a successful pairing:

Play/Pause/Answer phone call/End calling/Cancel a call: Click

Reject phone call: Hold the button A for about 2 seconds when there's an incoming call.

**Volume up/down:** Click button B/C turn up/down the volume. Switch songs: Hold the button B/C about 2 seconds to switch to the previous/next song. Switch between two input devices: When connecting to two input

devices, to switch the input, you need to first stop playback on the device that's playing and then manually start playback on the other device(or if it's already playing,the input will be switched automatically).

蓝牙耳机功率放大器 简体中文

以下状态将伴有提示音:开机、关机、配对、连接、清除配对、最大音量提 示音、最小音量提示音、低电提示、断开连接。

- ★请使用标准的5V充电器对其充电
- ★请勿将设备置于温度过高或过低(45℃以上0℃以下)的环境下
- ★请勿将设备接触液体溶液,以防造成设备严重损坏 ★当长期没有使用本品时,需要对产品进行充电,以保证电池寿命
- ★请先确认好合适音量后再戴上耳机享受音乐,以确保您的听力安全 ★请勿拆卸及损伤电池;请勿将电池投入火中;电池浸水后禁止使用

### 包装清单

BTR3K主机×1 Type C USB线×1 挂绳×1 快速入门×1 售后维修卡×1 可拆卸背夹×1

### 了解更多

若要了解有关产品信息请访问网www.fiio.com

产品名称:蓝牙耳机功率放大器 产品型号:BTR3K 额定输入:5V==500mA 重量:约23.5g(不含背夹) 执行标准:GB8898-2011

制造商:广州飞傲电子科技有限公司 地址:广州市白云区黄石西路石岗村后岗工业区F栋2楼

### 环保材料说明

# 产品中有害物质的名称及含量

|         | 有害物质      |           |           |                |               |                 |
|---------|-----------|-----------|-----------|----------------|---------------|-----------------|
| 部件名称    | 铅<br>(Pb) | 汞<br>(Hg) | 镉<br>(Cd) | 六价铬<br>(Cr,VI) | 多溴联苯<br>(PBB) | 多溴二苯醚<br>(PBDE) |
| PCB     | Х         | 0         | 0         | 0              | 0             | 0               |
| PCBA 焊点 | Х         | 0         | 0         | 0              | 0             | 0               |
| 元器件     | Х         | 0         | 0         | 0              | 0             | 0               |
| 显示屏*    | Х         | 0         | 0         | 0              | 0             | 0               |
| 电池*     | Х         | 0         | 0         | 0              | 0             | 0               |
| 外观件     | 0         | 0         | 0         | 0              | 0             | 0               |
| 配件*     | Х         | 0         | 0         | 0              | 0             | 0               |

注: 表中标记"X"的部件,皆因全球技术发展水平限制而无法实现有害 物质的替代。带\*号部件表示如果在您所购买的产品中无该部件,请忽 略表中该部件信息。

O: 表示该有害物质在该部件所有均质材料中的含量均在GB/T 26572-2011规定的限量要求以下。

X: 表示该有害物质至少在该部件的某一均质材料中的含 量超出 GB/T 26572-2011规定的限量要求。

根据中国电子行业标准SJ/T 11364-2014 和相关的中国政府法规,本 产品及其某些内部或者外部组件上可能带有环保使用期限标识。取决 于组件的组件制造商,产品及其组件上的使用期限标识可能有所不 同。组件上的使用期限标识优先于产品上任何与之相冲突的或不同的 环保使用期限标识。

10 此环保使用期限只适用于产品在规定的条件下工作。

由于产品不断改进,各项规格及设计随时更改,恕不另行通知。 Due to continuous improvement, every specification and design is subject to change at any time without further notice.

Bluetooth Headphone Amplifier

Bluetooth Headphone Amplifier

Activate Siri: Double click the button A.

# **Indicator Display**

1. Status indicator display (when not playing) Bluetooth Waiting Waiting

| Didetootii         | l Mairille I                                   | waiting to  | Connecte                | :u   |
|--------------------|--|---|-------------------------|--|
| Battery            | to pair  | reconnect   | Not playing             | playing  |
| Low battery        | Red light indicates the current working status |   |                         |  |
| Charging           | Red and<br>blue lights<br>flash<br>alternately | steadily on and<br>Blue light flashes<br>twice every 2<br>seconds (Red<br>light goes off<br>when Blue light | Blue light flashes      | Codec<br>indicator<br>light stays<br>steadily on |
| Normal state       |  | Blue light flashes  | Blue light flashes      |  |
| Charging completed |  | twice every 2<br>seconds  | once every 3<br>seconds | indicator<br>light pulses                        |

# 2. Indicator display of different input codecs (when playing)

| Codec            | Color of the indicator light |
|------------------|------------------------------|
| SBC              | Blue light pulsates          |
| AAC              | Cyanic Light pulsates        |
| aptX、<br>aptX LL | Purple light pulsates        |
| aptX HD          | Yellow light pulsates        |
| LDAC             | White light pulsates         |

# **Notification Sounds**

here will be notification sounds under the following status: Power on, power off, pair, connect, clear pairing history, Maximun volume, Minimun volume, low battery warning and pairing disconnected.

# **Notes and Precautions**

- ★It's recommended to charge the device using a standard 5V charger.
- ★Please don't place the device in circumstance of excessive high/low temperature (above 45°C or below 0°C)

★Please keep the device away from liquids to avoid any damage to

★If the device is to be left unused for a long time, please recharge it periodically to preserve its battery life

★Please adjust the volume to a suitable level before putting on the earphones to protect your hearing. ★Please do not disassemble, damage the battery, or drop it into

fire; it's prohibited to continue using after the battery is soaked in

# **List of Items Included**

 $BTR3K \times 1$ Type C USB cable  $\times 1$  Lanyard  $\times 1$ Quick start guide  $\times 1$  Removable rear clip  $\times 1$  Warranty card  $\times 1$ 

To learn more about the product, please visit our website: www.fiio.com.

# **WEEE Directive & Product Disposal**

At the end of its serviceable life, this produc should not be handed as household or general waste.It should be handed over to the applicable collection point for the recycling of electrical and electronic equipment, or returned to the supplier for Internal/Supplied Batteries

This symbol on the battery indicates that the battery is to be collected separately. This battery is designed for separate

collection at an appropriate collection point Qualcomm aptX is a product of Qualcomm Technologies, Inc. and/or its subsidiaries. Oualcomm is a trademark of Oualcomm Incorporated.

registered in the United States and other countries. aptX is a trademark of Qualcomm Technologies International, Ltd., registered in the United States and other countries. LDAC and LDAC logo are trademarks of Sony Corporation.

Qualcomm<sup>®</sup> aptX<sup>®</sup>HD